



Lingua RX 6/12

Lingua Digital Infrared Receiver 6/12 audio channels



Description

The lightweight and ergonomically designed Lingua RX digital infrared pocket receiver can receive up to 6 or 12 languages, has superior sound, and boasts a beautiful, ergonomic design.

Lingua RX Models

- ▶ 6 Channels **71.98.0205**
- ▶ 12 Channels **71.98.0206**

Design

From its strong lines and deep, radiant black color to its sleek profile, the Lingua RX has a stylish, contemporary design that adds a touch of elegance and discreet luster to any meeting. The

Lingua receiver's minimal interface removes all information clutter and informs users at a simple glance, with clear and direct information.

Greener Batteries

A large, bright, and crisp *OLED* screen displays the channel number, language name, and volume. A battery icon appears when the battery is low. In scanner mode, the screen also displays reception quality. The Lingua receiver can be powered via the rechargeable Li-ion battery pack with an autonomy of about 20 hours. The Lingua RX is equipped with an advanced green battery technology that dramatically reduces the cost of ownership while cutting down on the number of batteries in landfills.

Charging happens in the intelligent Lingua charging case that offers space to charge 64

receivers at once. The Lingua charger also has a LAN connection with a built-in web interface for Lingua RX configuration, statistics retrieval (battery health), and firmware updates.

To increase the battery lifespan, the Lingua receiver is switched off when the headphone is disconnected. When signal reception becomes too low, the audio is muted. If the receiver does not receive any valid IR signal for more than 1 min, it automatically switches to standby.

A Perfect Signal, Everywhere

The 270° wide reception angle and built-in error correction ensures a crystal-clear sound at all times. Reception is also impervious to high-frequency lighting and even remains optimal under bright sunlight.

The reception test mode can be used to easily check the radiator coverage.

Standards-compliant

The Lingua RX complies with IEC 61603-7 and IEC 60914 standards, which means it can be used with other, standards-compliant equipment.

Additional Functional Channels

Before the meeting starts a separate music channel can be distributed to all participants and in case of emergency, an evacuation message can be distributed to all channels

Mobility

A clip at the back of the receivers ensures that the Lingua RX is easy to carry around by attaching it to a piece of clothing.

Benefits

- 6 or 12 Audio channels
- Crystal-clear, interference-free audio
- Stylish and minimal design
- Green battery technology
- Plug-and-play setup
- Built-in connection for statistics, configuration & updates

Features

- Channel Up/Down buttons
- Volume Up/Down buttons

- OLED display with:
 - Channel number
 - Language
 - Volume bar
 - Battery status indication (if battery is low)
 - Reception status indication (in scanner mode)
- Operates on a Li-ion rechargeable battery pack (included)
- Standby mode when no headphone connected
- Audio muted when received signal is too low
- Pocket clip

Connectivity

- 3.5 mm jack plug for headphones

Headphones TEL152 **71.04.1216**

- Battery pack

Lingua Battery Pack **71.98.0234**

- Charging contacts

Lingua Charging Case **71.98.0235**

Models

The Lingua Receiver are available with 6 or 12 channels:

Lingua RX 6 Channels **71.98.0205**

Lingua RX 12 Channels **71.98.0206**

Certifications

Region	Certification
Europe	CE
World	IEC61603-7 IEC60914

Specifications

Mechanical	
Material	PC/ABS
Color	RAL9011
Size (mm)	50 (w) × 132 (h) × 20 (d) <i>clip included</i>
Weight (g)	110
Electrical	
Supply	Li-ion battery 3.7 V 1050 mAh
Audio quality	16 bit digital @ 44.1 kHz
Power consumption	200 mW
Sensitivity angle	270°
Battery Autonomy & Charging	
Capacity	1050 mAh
Autonomy	20 hours
Output voltage	3.7 V
Charging time	2 hours to 100%

All information copyright **Televic Conference**,
2017. Version 1.5, March 2017

—
Leo Bekaertlaan 1 · 8870 Izegem · Belgium
Tel. +32 51 30 30 45
Fax +32 51 31 06 70
E-mail: conference@televic.com
Web: <http://www.televic-conference.com>
*Televic reserves the right to change this document
without notice.*