

# SIMPLE AND SAFE AUDIO LINKS







Lightweight, compact and performing, the perfect combination of mobility, sound quality and ease of use.









Ethernet / 3G / 4G



2G / 3G / 4G









# Professional mobile phone with AoIP: Simple as a phone call!



# SIMPLICITY /



- Full Duplex
- Embedded HTML server for easy access to all parameters
- Network quality meters
- SIP or direct RTP
- Factory SIP account included
- Easy update by USB
- N/ACIP compliant (UER Tech 3326)

# **CONNECTIVITY**



- AoIP over wired Ethernet and Wi-Fi
- AoIP over 3G/4G-LTE mobile networks
- VoLTE
- Mobile voice over 2G/3G networks with HD Voice™ (7 kHz)
- **GPIO**

#### **SAFETY**



- FFC for secure connection
- Remote Access: remote access and control via Internet
- Adjustable Opus bitrate (12-192 kbit/s), during communication with no audio artefact, to fit bandwidth
- 2 antennas for better network reception
- > 5H autonomy with rechargeable NiMH batteries (6xAA), integrated charger
- Lockable power socket

# **AUDIO INTERFACES**



- Best in class audio pre-amplification
- 1 balanced mic/line input
- 1 balanced line input
- 1 balanced line output
- 2 headphones outputs
- 48V Phantom power







# **CODING ALGORITHMS**



#### Ethernet / 3G+ / 4G-LTE

OPUS (20 kHz), ajustable 12-192kbits/s / G722 (7 kHz); G711 (3 k



#### 2G / 3G / 3G UMTS / 4G AMR-WB, AMR-NB

# **AUDIO INTERFACES**

- 1 balanced mic/line input (XLR 3 pins)
- 1 balanced line input (XLR 3 pins)
- 2 headphone outputs (1 jack, 1 mini-jack)
- 1 balanced line output (combo 3 pins)

#### Mic / Line Inputs

- Selectable gain 0/16/32/48 dB + potentiometer
- Max gain: +70 dB
- Max input level: +19 dBu
- High-pass filter (50 Hz, 18dB/o)
- Limiter (-6 dBFS)
- 48V phantom power
- 4 selectable gains

#### Line Input

- Adjustable gain
- Clipping level: +4 dBu to +16 dBu

#### Line Output

- Adjustable gain (1 dB steps)
- Max level: +4 dBu to +22 dBu

#### **AUDIO PERFORMANCE**

- EIN < 126 dBu @ gain max.
- THD+N < -78 dB
- Frequency response: +/- 0.3 dB (20 20000 Hz)
- Noise gate and echo cancelling

#### **CONTROL AND SUPERVISION**

- Embedded HTML server, and remote control via Ethernet/IP
- AETA Remote Access: remote control via Internet
- Transmission of digital I/O (GPIO): 2 inputs, 2 outputs
- SNMP

#### **NETWORK INTERFACES**

- Ethernet 10/100BaseT IP / SIP
- Integrated mobile access 2G/3G/3G+/4G: IP data mode, voice/HD Voice
- SIM card slot, two SMA antenna sockets
- SIP or direct RTP
- + 100% FEC: packet replication (standard or interleaving)

#### **GENERAL**

- Power 10-16 VDC or standard batteries (6xAA-size)
- OLED screen
- Push/pull SIM card holder
- Phone Book
- Dimensions: 158 x 134 x 48 mm (W x D x H, overall). Rack mount version: 148x134x44 mm)
- Max weight 0.635 kg (batteries excluded)
- Max weight 0.804 kg (batteries included))
- Operating temperature range 0°- 45°C

#### **OPTIONS**

- Remote access
- Lockable power socket
- Permanent power
- DC reverse protection
- Scoop Manager

### 1 UNIT PACK

- Scoopfone 4G
- Lockable power socket
- Remote access
- Car 12V DC adapter
- Ni-MH battery set
- Carrying bag
- µSIM adapter

#### **ACCESSORIES**

- Carrying bag
- Ni-MH battery set
- Rack mount kit for ScoopFone 4G-R
- Blind front panel plate 1/3 of 19"
- Spare AC/DC power supply
- Car DC adapter
- Multiband antenna patch
- "T" Multiband antenna
- 1m & 3m cable multiband antenna
- µSIM card adapter

# Scoopfone + USCOOP pack

- Scoopfone 4G
  - + Lockable power socket
- µSC00P
  - Remote access
  - Car 12V DC adapter

# **2 UNITS PACK**

- Scoopfone 4G
- Lockable power socket
- Remote access
- Scoopfone 4G-R
  - Remote access
- Car 12V DC adapter
- Ni-MH battery set
- Carrying bag 2 µSIM adapters
- Rack mounting kit
- 2 blinding plates



Carrying bag (5 years warranty)

Centre d'affaires La Boursidière, rue de la boursidière BP82 / F-92357 Le Plessis Robinson - France Tél. +33 1 41 36 12 00 / Fax +33 1 41 36 12 69

sales@aeta-audio.com

Ni-MH battery set

Rack mounting kit

2 blinding plates

Carrying bag

2 µSIM adapter

**AFTER SALES SERVICE** aftersales@aeta-audio.com

www.aeta-audio.com